

## Create the future NXTR PM

### Specifications

			NXTR PM	NXTR PM with PM Smart Changer <sup>*1,2</sup>
Repeated alignment accuracy <sup>*3</sup>			±0.010 mm Cpk ≥ 2.0 (6σ)	±0.010 mm Cpk ≥ 2.0 (6σ)
Printing accuracy <sup>*3</sup>			±0.020 mm Cpk ≥ 2.0 (6σ)	±0.020 mm Cpk ≥ 2.0 (6σ)
Printing speed			1 to 300 mm/sec	1 to 300 mm/sec
Panel size (L x W)	Single conveyor	Single conveyance	48 x 48 mm to 610 x 610 mm	48 x 48 mm to 610 x 610 mm
	Double conveyor	Single conveyance	48 x 48 mm to 610 x 510 mm	48 x 48 mm to 610 x 510 mm
		Dual conveyance	48 x 48 mm to 330 x 280 mm	48 x 48 mm to 330 x 280 mm
Screen frame (L x W)			650 x 550 mm, 29 x 29 inch, 750 x 750 mm, 750 x 810 mm	29 x 29 inch, 750 x 750 mm
Backup block size			380 mm, 480 mm, 560 mm, 620 mm	48 x 38 mm to 330 x 270 mm
PM Smart Changer rack levels			-	4 levels
Weight			1,600 kg	1,800 kg
Power			3-phase AC 200 to 230 V ±10 V (50/60 Hz)	3-phase AC 200 to 230 V ±10 V (50/60 Hz)
Air				0.4 MPa

\*1 Option

\*2 When changing backup blocks automatically, backup blocks, backup exchange frames, and adapters that support PM Smart Changer are required.

\*3 Under optimum Fuji conditions.

The content is subject to change without notice due to constant product development.

The information is current as of January 2022.

©2022 FUJI CORPORATION. All Rights Reserved.